

Stückliste zum Schaltbild 561/I

SABA 351 GW

Nr.	Widerstände	Bestell-Nr.	Nr.	Kondensatoren	Bestell-Nr.
1			37	5 000 pF	442/33
2	Ma. 50 K Ohm	181/26	38	5 000 "	442/33
3	Dr. 300 "	382/V	39	5 000 "	442/33
4	Dr. 100 "	382/XV	40	5 000 "	442/33
5	Dr. 6000 "	383/XII	41	10 "	462/3
6	Ma. 5 K "	213/29	42	0,1 µF	442/77
7	Ma. Potentiom. 10 K "	560/51	43	0,1 "	
8	Dr. 600 "	382/IX	44	500 pF	442/57
9	Dr. 100 "	382/XV	45	5 200 "	442/33
10	Ma. 1 M "	112/68	46	10 "	462/3
11	Ma. 1 M "	112/68	47	0,1 µF	442/77
12	Ma. 1 M "	112/68	48	0,1 "	
13	Ma. 0,3 M "	213/30	49	5 200 pF	442/33
14	Ma. 0,3 M "	213/30	50	50 "	462/11
15	Dr. 3000 "	383/X	51	15 "	462/4
16	Ma. Potentiom. 1,5 M "	560/52	52	0,1 µF	442/71
17	Ma. 0,1 M "	138/28	53	100 pF	462/12
18	Ma. 0,1 M "	138/28	54	5 000 "	442/33
19	Ma. 0,1 M "	138/28	55	8 µF	452/3
20	Ma. 50 K "	181/26	56	3 000 pF	442/53
21	Ma. 1 M "	112/68	57	1 000 "	442/58
22	Ma. 1 K "	360/98	58	5 000 "	442/33
23	Dr. 150 "	382/XIV	59	5 000 "	442/33
24	Spannungsteiler 75/125 Ω	433/XI	60	0,5 µF	442/75
25	" 100/350 Ω	433/XII	61	0,1 "	442/52
26	Dr. 2000 Ohm	383/XIX	62	2 000 pF	442/59
27	Dr. 6000 "	383/XII	63	25 µF	452/6
28	Dr. 2000 "	383/XIX	64	0,1 "	442/72
29	Dr. 2000 "	383/XIX	65	2 "	561/82 α
30	Dr. 100 "	383/XXIV	66	32 "	430/70
31	Dr. 50 "	382/III	67	32 "	430/70
32	Dr. 9000 "	383/XIII			
33	Dr. 4000 "	383/XI			
34	Ma. 10 K "	138/30			
			Verschiedenes:		
			72	Siebdrossel	522/III
			73	Siebdrossel	455/VII
			74	Sicherung 0,35 Amp.	563/74
			75	Sicherung 0,35 Amp.	563/74
			76	Soffittenlampe 5 V 0,2 A	451/139
			77	Soffittenlampe 5 V 0,2 A	451/139
			78	Sicherung 120 mA	590/113
			79	Urdox 8 Volt 0,2 Amp.	451/140

Ma. = Massewiderstand Dr. = Drahtwiderstand